

ELECTRICAL :
MECHANICAL :
S/W VERSION :
MODEL CODE & I

CBM249

Midland 203

P A R T S L I S T

=====

SEQ	LEVEL	PART-NO.	NAME & DESCRIPTION	Q'TY	UT	KON	REFERENCE-NO
1	2	CBM249CO	COVER ASS'Y	1.000	EA		
	3	12-00000-83	SPEAKER	1.000	EA	SUB	SP1(SPEAKER)
	3	60-00008-01	MACHINE SCREW	4.000	EA	SUB	ESCUTCHEON & MAIN BODY:4
	3	60-00054-02	TAPPING SCREW	3.000	EA	SUB	SPK.MTG:3
	3	60-00064-02	TAP TITE SCREW	8.000	EA	SUB	COVER & MAIN BODY MTG
	3	74-00009-00	BOTTOM COVER	1.000	EA	SUB	
	3	74-00010-00	UPPER COVER	1.000	EA	SUB	
	3	72-00001-00	HOLDER SPEAKER	3.000	EA	SUB	SPK. MTG:3
	3	86-00012-02	E.S.C (Midland 203)	1.000	EA	SUB	
	3	83-00042-00	KNOB CONTROL	2.000	EA	SUB	
	3	83-00043-00	KNOB PUSH	1.000	EA	SUB	
	3	90-00006-00	FELT	1.000	EA	SUB	AIR VENT
	3	90-00007-00	FELT STICKER	2.000	EA	SUB	COVER MTG(REAR)
	3	84-00027-00	LENS	1.000	EA	SUB	
	3	79-00010-02	CLIP LOCK	7.000	EA	SUB	
2	2	CBM249XTL	CRYSTAL ASS'Y	1.000	EA		
	3	07-00001-01	CRYSTAL	1.000	EA	MAN	X1
	3	07-00030-01	CRYSTAL	1.000	EA	MAN	X2
3	2	CBM249FB	FRONT BODY ASS'Y	1.000	EA		
	3	01-00047-01	DISK CERAMIC	1.000	EA	SUB	C116A
	3	01-00073-01	DISK CERAMIC	1.000	EA	SUB	C31
	3	03-00035-00	TRANSISTOR	1.000	EA	SUB	Q26
	3	10-00028-01	I.C	1.000	EA	SUB	IC3
	3	20-00002-00	JACK DC	1.000	EA	MAN	JK1(EXT)
	3	15-00005-01	CONNECTOR	1.000	EA	SUB	JK4(ANT)
	3	24-00008-00	HARNESS ASS'Y (CURLED CORD)	1.000	EA	SUB	
	3	26-00001-00	MICA	1.000	EA	SUB	TR 2SC2078
	3	60-00028-01	MACHINE SCREW	3.000	EA	SUB	TR MTG:2 , IC MTG:1
	3	60-00038-02	TAPPING SCREW	2.000	EA	SUB	SUB PCB MTG:2
	3	60-00053-02	TAPPING SCREW	4.000	EA	SUB	MAIN PCB:4
	3	62-00004-00	NUT	3.000	EA	SUB	TR MTG : 2 , IC MTG : 1
	3	62-00006-00	NUT	2.000	EA	SUB	FOR VOL , SQ
	3	63-00014-00	WASHER SPRING	3.000	EA	SUB	TR MT : 2 , IC MTG : 1
	3	70-00012-00	MAIN BODY	1.000	EA	SUB	
	3	73-00003-00	HEAT SINK	1.000	EA	SUB	
	3	75-00037-00	LUG TERMINAL	2.000	EA	SUB	
	3	76-00070-00	SHIELD PLATE	1.000	EA	SUB	
	3	82-00013-00	CORD STOPPER	1.000	EA	SUB	
	3	85-00014-00	BUSHING	1.000	EA	SUB	TR 2SC2078
	3	90-00004-00	FELT	2.000	EA	SUB	FOR SLIDE SW
	3	92-00012-00	COPPER TAPE	2.000	EA	SUB	
4	2	CBM249MA	MIC ASS'Y	1.000	EA		
	3	01-00074-00	CHIP CERAMIC	1.000	EA	SUB	C41
	3	13-00000-00	MIC CONDENSER	1.000	EA	SUB	
	3	24-00002-00	CURLED CORD	1.000	EA	SUB	
	3	15-00004-01	CONNECTOR PLUG	1.000	EA	SUB	
	3	32-00009-11	SWITCH VOLUME	1.000	EA	SUB	SW5
	3	60-00003-03	SCREW(SECURING)	2.000	EA	SUB	
	3	60-00036-02	TAPING SCREW	4.000	EA	SUB	
	3	60-00038-02	TAPPING SCREW	3.000	EA	SUB	
	3	60-00056-02	TAPPING SCREW	2.000	EA	SUB	
	3	60-00061-02	TAPPING SCREW	3.000	EA	SUB	
	3	60-00069-02	WOOD SCREW	1.000	EA	SUB	
	3	63-00002-00	WASHER	2.000	EA	SUB	
	3	63-00020-00	WASHER	2.000	EA	SUB	
	3	63-00022-00	WASHER	3.000	EA	SUB	
	3	81-00007-00	UPPER COVER(MIC)	1.000	EA	SUB	
	3	81-00010-00	BOTTOM COVER (MIC)	1.000	EA	SUB	
	3	71-00001-00	BRACKET(MIC MTG)	1.000	EA	SUB	

3	71-00017-00	BRACKET(SET MTG)	SECC T=1.6 BLACK-PAINT	1.000	EA	SUB	
3	82-00001-00	HOLDER MIC	PC BLK	1.000	EA	SUB	
3	82-00010-00	LEVER(MIC)	PC BLACK	1.000	EA	SUB	
3	95-00003-00	NAME PLATE(MIC)	ALP3 11X36XT=0.4MM.	1.000	EA	SUB	
3	95-00015-00	NAME PLATE(MIC)	PVC 12.8x23.9xT0.4 CLEAR	1.000	EA	SUB	
3	85-00004-00	BEZEL	ABS BLK	1.000	EA	SUB	
3	85-00011-00	GRILL CAP	ABS 94HB L380-9001 BLK	1.000	EA	SUB	
3	85-00024-00	WIRE CLAMP (CORD)	NYLON	1.000	EA	SUB	
3	89-00013-00	CUSHION	Ø22xT4 SPONGE STICKER	1.000	EA	SUB	
3	89-00028-00	RUBBER	RUBBER BLACK Ø9.5XØ30XT18.2MM.	1.000	EA	SUB	
3	90-00005-00	FELT	FELT 34x36xT=0.15MM	1.000	EA	SUB	
3	97-00014-00	BOX MIC	SW2E 221(W)X70(D)X	1.000	EA	FIN	
3	98-00005-02	CELLOPHANE	P.P CELLOPHANE 100X100XT0.05MM.	2.000	EA	FIN	ACCESSORY MIC:1,ACCESSORY SCREW:1
3	98-00013-03	CELLOPHANE	P.P CELLOPHANE 100X200XT0.05MM.	1.000	EA	FIN	MICROPHONE:1
5	2	CBM249MPA MAIN PCB AUTO ASS'Y		1.000	EA		
3	01-00004-11	ELECT CAPACITOR	1UF 50V 20% 5X11	2.000	EA	AUT	C146.147
3	01-00006-11	ELECT CAPACITOR	10UF 16V 20% 5X11	5.000	EA	AUT	C2.53.142.151.CA1
3	01-00010-11	ELECT CAPACITOR	1000UF 16V 20% 10X16	1.000	EA	AUT	C48
3	01-00012-11	ELECT CAPACITOR	100UF 16V 20% 6.3X11	3.000	EA	AUT	C40.69.70
3	01-00018-11	ELECT CAPACITOR	22UF 16V 20% 5X11	5.000	EA	AUT	C33A.34.59.131.202
3	01-00017-11	ELECT CAPACITOR	2.2UF 50V 20% 5X11	1.000	EA	AUT	C18
3	01-00022-11	ELECT CAPACITOR	220UF 16V 20% 6.3X11	1.000	EA	AUT	C52
3	01-00027-11	ELECT CAPACITOR	33UF 16V 20% 5X11	3.000	EA	AUT	C47.67.68
3	01-00036-11	ELECT CAPACITOR	470UF 16V 8x12	2.000	EA	AUT	C32.49
3	01-00029-11	ELECT CAPACITOR	4.7UF 50V 20% 5X11	2.000	EA	AUT	C28.42
3	01-00034-11	ELECT CAPACITOR	47UF 16V 20% 5X11	3.000	EA	AUT	C33.62.66
3	05-00001-31	DIODE RECTIFIER	1N4004	2.000	EA	AUT	D11.12
6	2	CBM249MPM MAIN PCB MANUAL ASS'Y		1.000	EA		
3	00-00109-00	FILM RESISTOR	1 1/ 8W 5% ST	1.000	EA	MAN	R127
3	00-00101-02	FILM RESISTOR	100 1/ 2W 5% ST MINI	1.000	EA	MAN	R94
3	00-00120-81	METAL OXIDE RESISTOR	12 2W 5% ST	1.000	EA	MAN	R42
3	00-00229-81	METAL OXIDE RESISTOR	2.2 Ohm 2W 5%	1.000	EA	MAN	R152
3	00-00472-02	FILM RESISTOR	4.7K 1/ 2W 5% ST MINI	1.000	EA	MAN	R129
3	00-00221-80	METAL OXIDE RESISTOR	220 1W 5% ST	2.000	EA	MAN	R128.210
3	00-005R6-81	METAL OXIDE RESISTOR	5.6 2W 5% (MOR02WJ056JA10)	1.000	EA	MAN	R72
3	03-00026-00	TRANSISTOR	KTC1006	1.000	EA	MAN	Q25
3	08-00001-01	CERAMIC FILTER	LT455HTU	1.000	EA	MAN	CF2
3	08-00004-01	FILTER CERAMIC	LT10.7MJ (RED)	1.000	EA	MAN	CF1
3	02-00012-01	TRANSFORMER	EI-24	1.000	EA	MAN	T6
3	02-00004-01	TRANSFORMER	EI-19	1.000	EA	MAN	L9
3	02-00000-31	COIL AXIAL	AL0307-2R2K	2.000	EA	MAN	L1.2
3	02-00003-31	COIL AXIAL	0.47UH:LAL03TBR47K	1.000	EA	MAN	L4
3	02-00006-21	COIL SPRING	5X0.6X13.5T:R	1.000	EA	MAN	L6
3	02-00067-21	COIL SPRING	6.0X0.9X8.5T:R	2.000	EA	MAN	L7.8
3	02-00068-21	COIL SPRING	4.5X0.9X8.5T:R	1.000	EA	MAN	L5
3	02-00069-21	COIL MOLD	COIL MOLD BALANCE 8.5T	1.000	EA	MAN	L3
3	02-00061-81	COIL IFT	RF COIL RX 83A	1.000	EA	MAN	T1
3	02-00062-81	COIL IFT	RF COIL RX 7252	1.000	EA	MAN	T2
3	02-00063-81	COIL IFT	RF COIL RX 7255	3.000	EA	MAN	T3.8.9
3	02-00064-81	COIL IFT	AM COIL RX 7224	1.000	EA	MAN	T4
3	02-00065-81	COIL IFT	AM COIL RX 7223	1.000	EA	MAN	T5
3	02-00066-81	COIL IFT	VCO COIL 7046	1.000	EA	MAN	T7
3	02-00067-81	COIL IFT	RF COIL 7014	1.000	EA	MAN	T10
3	02-00068-81	COIL IFT	FM COIL 5002	1.000	EA	MAN	T11
3	03-00019-00	TRANSISTOR	KTB1367	2.000	EA	MAN	Q35.42
3	05-00010-01	ZENER DIODE	1N5232B (5.6V)	2.000	EA	MAN	D5.18
3	05-00011-01	ZENER DIODE	1N5237B (8.2V)	1.000	EA	MAN	D15
7	2	CBM249MPS MAIN PCB SMD ASS'Y		1.000	EA		
3	00-00000-15	CHIP RESISTOR	0 1/16W 5% T 1608	2.000	EA	SMD	R43.143
3	00-001R0-15	CHIP RESISTOR	1 1/16W 5% T 1608	1.000	EA	SMD	R69
3	00-00100-15	CHIP RESISTOR	10 1/16W 5% T 1608	3.000	EA	SMD	R4.68.125
3	00-00101-15	CHIP RESISTOR	100 1/16W 5% T 1608	4.000	EA	SMD	R6.118.123.149
3	00-00102-15	CHIP RESISTOR	1K 1/16W 5% T 1608	11.000	EA	SMD	R13.29.30.35.70.75.92.111.112.124.
						SMD	176
3	00-00103-15	CHIP RESISTOR	10K 1/16W 5% T 1608	31.000	EA	SMD	R3.7.12.22.52.54.74.83.88.89.91.93.100.
						SMD	101.102.115.119.140.141.146.150.155.156.

3	00-00104-15	CHIP RESISTOR	100K 1/16W 5% T 1608	8.000	EA	SMD	157.158.161.164.165.166.178.180
3	00-00122-15	CHIP RESISTOR	1.2K 1/16W 5% T 1608	3.000	EA	SMD	R11.60.62.103.145.148.168.169
3	00-00124-15	CHIP RESISTOR	120K 1/16W 5% T 1608	1.000	EA	SMD	R2.17.47
3	00-00123-15	CHIP RESISTOR	12K 1/16W 5% T 1608	2.000	EA	SMD	R109
3	00-00150-15	CHIP RESISTOR	15 1/16W 5% T 1608	1.000	EA	SMD	R46.55
3	00-00152-15	CHIP RESISTOR	1.5K 1/16W 5% T 1608	1.000	EA	SMD	R126
3	00-00153-15	CHIP RESISTOR	15K 1/16W 5% T 1608	1.000	EA	SMD	R40
3	00-00154-15	CHIP RESISTOR	150K 1/16W 5% T 1608	5.000	EA	SMD	R33.41.64.66.82
3	00-00183-15	CHIP RESISTOR	18K 1/16W 5% T 1608	1.000	EA	SMD	R97
3	00-00182-15	CHIP RESISTOR	1.8K 1/16W 5% T 1608	2.000	EA	SMD	R56.172
3	00-00184-15	CHIP RESISTOR	180K 1/16W 5% T 1608	2.000	EA	SMD	R78.80
3	00-00203-15	CHIP RESISTOR	20K 1/16W 5% T 1608	1.000	EA	SMD	R106
3	00-00220-15	CHIP RESISTOR	22 1/16W 5% T 1608	1.000	EA	SMD	R144
3	00-00222-15	CHIP RESISTOR	2.2K 1/16W 5% T 1608	1.000	EA	SMD	R39
3	00-00223-15	CHIP RESISTOR	22K 1/16W 5% T 1608	5.000	EA	SMD	R31.73.76.77.162
3	00-00221-15	CHIP RESISTOR	220 1/16W 5% T 1608	5.000	EA	SMD	R16.53.67.84.85
				13.000	EA	SMD	R34.63.71.95.122.133.134.135.136.137.
						SMD	138.139.159
3	00-00224-15	CHIP RESISTOR	220K 1/16W 5% T 1608	7.000	EA	SMD	R19.24.27.32.36.167.170
3	00-00272-15	CHIP RESISTOR	2.7K 1/16W 5% T 1608	3.000	EA	SMD	R15.108.120
3	00-00275-15	CHIP RESISTOR	2.7M 1/16W 5% 1608	1.000	EA	SMD	R48
3	00-00331-15	CHIP RESISTOR	330 1/16W 5% T 1608	2.000	EA	SMD	R8.117
3	00-00332-15	CHIP RESISTOR	3.3K 1/16W 5% T 1608	4.000	EA	SMD	R96.116.154.183
3	00-00333-15	CHIP RESISTOR	33K 1/16W 5% T 1608	6.000	EA	SMD	R38.44.49.58.61.147
3	00-00393-15	CHIP RESISTOR	39K 1/16W 5% T 1608	1.000	EA	SMD	R20
3	00-00470-15	CHIP RESISTOR	47 1/16W 5% T 1608	1.000	EA	SMD	R151
3	00-00471-15	CHIP RESISTOR	470 1/16W 5% T 1608	5.000	EA	SMD	R18.25.107.130.132
3	00-00472-15	CHIP RESISTOR	4.7K 1/16W 5% T 1608	7.000	EA	SMD	R14.45.51.90.105.114.177
3	00-00473-15	CHIP RESISTOR	47K 1/16W 5% T 1608	5.000	EA	SMD	R26.65.86.131.217
3	00-00474-15	CHIP RESISTOR	470K 1/16W 5% T 1608	2.000	EA	SMD	R163.175
3	00-00561-15	CHIP RESISTOR	560 1/16W 5% T 1608	2.000	EA	SMD	R1.5
3	00-00562-15	CHIP RESISTOR	5.6K 1/16W 5% T 1608	3.000	EA	SMD	R104.181.182
3	00-00681-15	CHIP RESISTOR	680 1/16W 5% T 1608	5.000	EA	SMD	R9.10.23.87.113
3	00-00682-15	CHIP RESISTOR	6.8K 1/16W 5% T 1608	1.000	EA	SMD	R21
3	00-00683-15	CHIP RESISTOR	68K 1/16W 5% T 1608	4.000	EA	SMD	R37.99.173.174
3	00-00823-15	CHIP RESISTOR	82K 1/16W 5% T 1608	3.000	EA	SMD	R28.57.59
3	00-00822-15	CHIP RESISTOR	8.2K 1/16W 5% T 1608	2.000	EA	SMD	R50.98
3	00-00821-15	CHIP RESISTOR	820 1/16W 5% T 1608	2.000	EA	SMD	R110.121
3	01-00072-00	CHIP CERAMIC	0.01UF GRM39 X7R103K 25	24.000	EA	SMD	C13.7.9.12.13.15.16.19.21.30.57.64.
						SMD	90.95.98.99.100.104.118.132.135.
						SMD	149.175
3	01-00074-00	CHIP CERAMIC	0.001UF GRM39 X7R102K 50	11.000	EA	SMD	C14.17.36.38.84.91.119.136.139.143.203
3	01-00077-00	CHIP CERAMIC	0.1UF GRM39 X7R104K 16	4.000	EA	SMD	C50.51.71.130
3	01-00059-00	CHIP CERAMIC	0.015UF GRM39 X7R153K 25	2.000	EA	SMD	C43.45
3	01-00005-00	CHIP CERAMIC	0.022UF GRM39 X7R223K 50	16.000	EA	SMD	C20.22.23.26.27.35.37.39.60.65.78.
						SMD	105.109.117.137.150
3	01-00003-00	CHIP CERAMIC	0.0022UF GRM39 X7R222J 50	1.000	EA	SMD	C25
3	01-00008-00	CHIP CERAMIC	0.027UF GRM39 X7R273K 25	1.000	EA	SMD	C79
3	01-00020-00	CHIP CERAMIC	0.0033UF GRM39 X7R332K 50	3.000	EA	SMD	C54.55.56
3	01-00300-00	CHIP CERAMIC	0.039UF GRM39 Y5V 393Z 50V	2.000	EA	SMD	C144.145
3	01-00030-00	CHIP CERAMIC	0.0047UF GRM39 X7R472K 50	8.000	EA	SMD	C44.46.63.74.81.92.120.193
3	01-00031-00	CHIP CERAMIC	0.047UF GRM39 Y5V473Z 25	5.000	EA	SMD	C11.111.138.141.148
3	01-00055-00	CHIP CERAMIC	0.068UF GRM39 X7R683K 16	1.000	EA	SMD	C224
3	01-00107-00	CHIP CERAMIC	1UF GRM39 Y5V105Z 10	3.000	EA	SMD	C58.73.167
3	01-00095-00	CHIP CERAMIC	100PF GRM39 COG101J 50	6.000	EA	SMD	C10.80.97.108.133.140
3	01-00112-00	CHIP CERAMIC	12PF GRM39 COG120J 50	1.000	EA	SMD	C6
3	01-00114-00	CHIP CERAMIC	120PF GRM39 COG121J 50	3.000	EA	SMD	C88.112.121
3	01-00130-00	CHIP CERAMIC	150PF GRM39 COG151J 50	2.000	EA	SMD	C86.113
3	01-00135-00	CHIP CERAMIC	16PF GRM39 COG160J 50	1.000	EA	SMD	C124
3	01-00147-00	CHIP CERAMIC	2PF GRM39 COG020C 50	1.000	EA	SMD	C8
3	01-00158-00	CHIP CERAMIC	22PF GRM39 COG220J 50	1.000	EA	SMD	C61
3	01-00159-00	CHIP CERAMIC	220PF GRM39 COG221J 50	2.000	EA	SMD	C103.115
3	01-00174-00	CHIP CERAMIC	27PF GRM39 COG270J 50	1.000	EA	SMD	C96
3	01-00192-00	CHIP CERAMIC	33PF GRM39 COG330J 50	1.000	EA	SMD	C122
3	01-00201-00	CHIP CERAMIC	39PF GRM39 COG390J 50	1.000	EA	SMD	C5
3	01-00194-00	CHIP CERAMIC	330PF GRM39 COG331J 50	2.000	EA	SMD	C106.129

3	01-00212-00	CHIP CERAMIC	4PF	GRM39 COG040C 50	1.000	EA	SMD	C94
3	01-00221-00	CHIP CERAMIC	4.7PF	GRM39 COG4R7C 50	1.000	EA	SMD	C152
3	01-00222-00	CHIP CERAMIC	47PF	GRM39 COG470J 50	5.000	EA	SMD	C41A.87.101.114.127
3	01-00243-00	CHIP CERAMIC	56PF	GRM39 COG560J 50	2.000	EA	SMD	C72.93
3	01-00260-00	CHIP CERAMIC	68PF	GRM39 COG680J 50	3.000	EA	SMD	C24.107.110
3	01-00269-00	CHIP CERAMIC	7PF	GRM39 COG070D 50	1.000	EA	SMD	C102
3	01-00286-00	CHIP CERAMIC	9PF	GRM39 COG090D 50	1.000	EA	SMD	C85
3	01-00004-20	CHIP TANTALUM	0.47UF	293D47X0025A2T25	1.000	EA	SMD	C83
3	01-00000-40	CHIP TRIMMER	20PF	STC3M20-T1	3.000	EA	SMD	TC1.2.3
3	03-00052-01	BRT	KRC102S		2.000	EA	SMD	Q33.36
3	03-00056-01	TRANSISTOR	KTA1505SY		5.000	EA	SMD	Q8.16.27.28.34
3	03-00058-01	TRANSISTOR	KTC3875S(GR)		17.000	EA	SMD	Q9.10.11.13.14.15.17.20.21. SMD 22.23.24.29.30.31.37.43
3	03-00057-01	TRANSISTOR	KTA1504SY		3.000	EA	SMD	Q1.12.32
3	03-00063-01	TRANSISTOR	2SC5345SY		12.000	EA	SMD	Q2.3.4.5.6.7.18.19.38.39.40.41
3	10-00027-00	I.C FM IF	SL5019		1.000	EA	SMD	IC4
3	10-00060-00	I.C OP AMP	KIA4558F		1.000	EA	SMD	IC2
3	10-00084-00	I.C PLL	GP214D		1.000	EA	SMD	IC6
3	10-00028-10	IC CPU	MB95F203KPF-G-SNE2		1.000	EA	SMD	IC1
3	05-00001-10	DIODE VARICAP CHIP	KDV251S (Q3D)		2.000	EA	SMD	D19.25
3	05-00003-40	DIODE SI CHIP	KDS184S		14.000	EA	SMD	D1.2.3.4.6.7.8.9.10.13.14.16.17.23
3	05-00002-40	DIODE SI CHIP	KDS226		1.000	EA	SMD	D21
3	17-02472-10	POTENTIOMETER CHIP	VG039NCHXTB472-PBF		4.000	EA	SMD	RV1.2.3.4
3	33-00040-00	P.C.B ASS'Y	129 X 179.5 X 1.6 FR4 1/1		1.000	EA	SMD	
4	18-00047-02	P.C.B MAIN	114 X 150.9 X 1.6 FR4 1/1		1.000	EA	SMD	
4	18-00106-03	P.C.B SUB ESC	55 X 30 X 1.6 FR4 1/1		1.000	EA	SMD	
4	18-00107-03	P.C.B SUB VOLUME	36.4 X 13.6 X 1.6 FR4 1/1		1.000	EA	SMD	
4	18-00111-03	P.C.B SUB MIC	17 X 27 X 1.6 FR4 1/1		1.000	EA	SUB	
8	2	CBM249PA	PACKING ASS'Y		1.000	EA		
3	96-00085-00	LABEL SERIAL	ART PAPER STICKER 30x45MM.		1.000	EA	FIN	
3	97-00142-00	TRAY BOX PULP MOLD	N30&C70 160Wx232Lx52H MM.		1.000	EA	FIN	
3	97-00144-02	OUT BOX	DW BC 376(W)x240(D)x236(H)		0.167	EA	FIN	
3	98-00013-05	CELLOPHANE	P.P CELLOPHANE 250X350XT0.05MM.		1.000	EA	FIN	FOR UNIT
3	97-00143-01	INNER BOX	SWE 236(W)x232(D)x58(H)		1.000	EA	FIN	
3	50-00072-00	MANUAL SET ASS'Y			1.000	EA	FIN	
4	93-00089-00	OWNER'S MANUAL	ART & WOODFREE PAPER 148X210 MM.		1.000	EA	FIN	
4	96-00190-00	ADESIVO CONSUMER BIANCO LABEL	HOLOGREM PAPER 50x160MM		1.000	EA	FIN	
4	93-00090-00	RTTE BOOKLET	WOOD FREE PAPER 210x120MM.		1.000	EA	FIN	
4	94-00061-02	MINI PANORAMA CATALOGUE	ART CARD 105x150 MM.		1.000	EA	FIN	
4	94-00080-00	DECLARATION OF CONFORMITY CARD	WOOD FREE PAPER 210x148MM.		1.000	EA	FIN	
4	98-00016-00	CELLOPHANE	P.P CELLOPHANE 160X250XT0.05MM.		1.000	EA	FIN	
3	96-00156-01	NAME LABEL	POLYESTER 21X44XT=0.15MM.		1.000	EA	FIN	
9	2	CBM249SPS	SUB PCB SMD ASS'Y		1.000	EA		
3	32-00004-20	SWITCH TACT	6x6x5.0H SMD (REEL)		2.000	EA	SMD	SW3.4
10	2	CBM249SPM	SUB PCB MANUAL ASS'Y		1.000	EA		
3	06-00020-01	LED LAMP	523ID		1.000	EA	MAN	LD3(TX)
3	06-00021-01	LED LAMP	523GD		1.000	EA	MAN	LD2(RX)
3	06-00008-51	LED DISPLAY	MLS-3203BHG1-B10 (GREEN)		1.000	EA	MAN	LD1(DISPLAY)
3	15-00034-01	CONNECTOR	SCN-16-4 PCB(R)		1.000	EA	MAN	JK3
3	16-00009-00	FLAT WIRE CABLE	7PIN 88MM 2.5PITCH		1.000	EA	MAN	CON1
3	32-00007-01	SLIDE SWITCH	SS-22F06(2P2T)		1.000	EA	MAN	SW1
3	32-00008-01	SLIDE SWITCH	SS-23D02-T 2P3T		1.000	EA	MAN	SW2
3	17-0B103-01	VR	F-09115N W10K L15KQ(L)		1.000	EA	MAN	VR1(SQ)
3	17-0A103-01	VR	RD915S-2A1-A103-0G48		1.000	EA	MAN	VR2(VOL)
3	95-00026-00	LED FILM	PC CLEAR 15.5x15 T=0.2MM.		1.000	EA	FIN	
11	2	CBM249WCA	WIRE COVER ASS'Y		1.000	EA		
3	16-00026-07	WIRE	1007 AWG 26(7/0.16) YEL		0.160	ME	SUB	PCB SP(+)--SP(+) 0.5:0.5
3	16-00027-07	WIRE	1007 AWG 26(7/0.16) GRN		0.160	ME	SUB	PCB SP(-)--SP(-) 0.5:0.5
12	2	CBM249WMA	WIRE MIC ASS'Y		1.000	EA		
3	16-00026-07	WIRE	1007 AWG 26(7/0.16) YEL		0.060	ME	SUB	PUSH SW ---CONDENSER MIC 0.5:0.5
3	16-00027-07	WIRE	1007 AWG 26(7/0.16) GRN		0.060	ME	SUB	PUSH SW --- CONDENSER MIC 0.5:0.5